
KSM-1322 Sub-miniature Reed Switch Form A, Center Contact, Release AT Configurable



This form A reed switch is built with a 2.25 mm diameter glass having a higher wall thickness for better glass to metal seals, and is a good solution for general purpose, high volume applications with a little shock and vibration, such as toys. The centre contact also makes it suitable for coil applications. The three differential ranges available cover a wide range of release specific applications. A specially plated contact for 230 VAC line voltage switching is also available.

Formations Available

-	,- 1		ţ,		-	
Cropped	SMD	Welded	Soldered	Goal post	L Formed	

Applications

This reed switch is suitable for use in the following applications and in many others: copiers and scanners, coffee machines, flow sensing, inclination sensors, lake current measurement, power switches in explosive areas, ferrous metal detection sensors, gear speed and direction sensors...

E	ectrical	

Contact Rating (max)	W/VA	10.0
Switching Current (max)	А	0.5
Carry Current (max)	А	1.5
Switching Voltage (max)	V _{DC}	180
Switching Voltage (max)	V _{AC}	130
Breakdown Voltage	V _{DC}	200
Initial Contact Resistance (max)	mΩ	150
Insulation Resistance (min)	Ω	10 ¹¹
Capacitance (min)	рF	0.2

Miscellaneous

Operate Time (max)	ms	0.5
Bounce Time (max)	ms	0.15
Release Time (max)	ms	0.15
Resonance Frequency	Hz	>2000
Operating Frequency	Hz	500
Operating Temperature	°C	-40 to +200
Test Coil		717 102 002

Ordering Code

KSM-1322-(Sub Code)-(Start Operate AT)-(Finish Operate AT)

Sub Code		L	М	Н	AC	
Release Range	AT	4 - 20	6 – 25	7.5 – 30	6 - 25	
Operate Range	AT	10 - 40	10 - 40	10 - 40	20 - 40	
Initial CR (max)	mΩ	100	120	150	150	
Contact Rating	W/VA	10	10	10	30	
Switching Voltage	Vac	130	130	130	230	

Ordering Example

KSM-1322-M-10-14 Denotes 10-14 Operate AT band, with a minimum Release AT of 6.

Other Special Configurations Available

Dynamic contact resistance limit Higher insulation resistance Special release limits Gold plates leads

Please refer to our reed switch usage notes

Due to continual improvement, specifications are subject to change without notice www.reed-sensor.co.kr

26 May 2004